

JE40 RAM enjoy radio system eRS4

enjoy motors®: electrónico - electronic - elettronico - electronique - elektronisch - eletrônico



Español:

JE40RAM (eRS4) es un motor con final de carrera electrónico y receptor radio integrado 433.92 MHz. Está especialmente diseñado para ser instalado en persianas con cajón de aluminio o pvc, persianas enrollables tradicionales y toldos verticales o persianas venecianas.

- Final de carrera electrónico con receptor integrado.
- Sistema Rolling Code. Frecuencia 433.92 MHz.
- Sencilla programación de los finales de carrera desde el emisor.
- Punto intermedio fácilmente programable.
- Memorización de nuevos emisores a través del original.
- Posibilidad de conexión a un pulsador unipolar.
- Posibilidad de funcionamiento tipo "paso a paso".
- Potencia: 10 Nm - 14 Rpm.

English:

JE40RAM (eRS4) is a motor with electronic limit switch and built in receiver 433.92 MHz. It has been designed to be installed with roller shutters in aluminium or pvc window shutter box, traditional roller shutter system, vertical awning or venetian blind.

- Electronic limit switch built in receiver.
- Rolling Code system. Frequency 433.92 MHz.
- Simple set up limit switch through emitter.
- Easily set up limit switch midpoint.
- Programming new transmitters, through the original one.
- Possibility to connect to unipolar pushbutton.
- Possibility to work type "step by step".
- Torque: 10 Nm - 14 Rpm.



Características principales - Main characteristics - Caratteristiche principali - Caratteristiche principali - Schlüsseleigenschaften - Características principais

Product Code	JE40/10RAM
Torque (Nm)	10
Speed (Rpm)	14
Tube diameter motor (Ø mm)	35
Max. load in Ø 40 mm tube	27
Working time (Minutes)	4
Limit switch capacity (Turns)	0 ~ ∞
Protection rating (IP)	IP44
Voltage ~ Frequency (V ~ Hz)	230 ~ 50
Absortion (A)	0,49
Consumption (W)	116
Cable length (M)	2,50
Motor weight (Kg)	1,35
Motor length (mm)	560
Package quantity (pcs)	10
Certification - Warranty	CE enjoy 6